










## KV-500 500W DC to AC Power Inverter

### Features:

- Compact Size, Light Weight & High Efficiency
- Low Battery Auto Shutdown
- Low Battery Alarm
- Overload and Short Circuit Protection
- Input Polarity Reverse Protection by Fuse
- High Surge Current Capacity. Easy to Start for TV, Motors & Other Inductive Load

### Specification:

KV-500	Model Number	KV-500
 <p><b>OUTPUT RECEPTACLES</b></p>    <p>Type-1   Type-2   Type-3</p>    <p>Type-4   Type-5   Type-6</p>  <p>Type-7</p>		
	Voltage In	12VDC or 24VDC
	Voltage Out	100V, 115V, 220V, 230V or 240V AC
	Continuous Power	500W
	Peak Power	1200W
	Output Frequency	50Hz or 60Hz
	Output Waveform	Modified Sine Wave
	No Load Current Draw	0.6A
	Efficiency	90%
	Fuse	30A x 2
	Weight	1.1kg
		Dimension